

## Other commands

<b>ARM A</b>	Part sets system A
<b>ARM B</b>	Part sets system B
<b>SET A</b>	Same as <b>ARM A</b> (if you prefer to use the word "set")
<b>SET B</b>	Same as <b>ARM B</b> (if you prefer to use the word "set")
<i>Note: Ask your installer if you are permitted to inhibit zones, tampers and faults</i>	
<b>FORCE</b>	This forces the panel into the Set mode and inhibits any open zones, tampers or faults
<b>FORCE A</b>	This forces the panel into the Part-Set A mode and inhibits any open zones, tampers or faults
<b>FORCE B</b>	This forces the panel into the Part-Set B mode and inhibits any open zones, tampers or faults

*Alternatively you can inhibit zones and tampers with the following commands...*

<b>SET **</b>	Inhibits all open zones before setting the system
<b>SET ##</b>	Inhibits all open tampers before setting the system
<b>SET *3</b>	Inhibits a specific zone (in this example zone 3)
<b>SET *z3</b>	This command is the same as set *3 above
<b>SET *z03</b>	This command is the same as set *3 above
<b>SET *z003</b>	This command is the same as set *3 above
<b>SET #3</b>	Inhibits a specific tamper circuit (in this example tamper 3)
<b>SET #z3</b>	This command is the same as set #3 above
<b>SET #z03</b>	This command is the same as set #3 above
<b>SET #z003</b>	This command is the same as set #3 above
<b>SET *p80</b>	Inhibits a specific point-zone (in this example point 80)
<b>SET #p80</b>	Inhibit a specific point-tamper (in this example pointer 80)

 **Note:** There is a one hour security lockout after seven wrong text commands and/or user codes



# GSM-Q

## User Manual

Safe & Secure

**SecureWave**  
868MHz Radio

www.hkc.ie

# Security

## Arming your system

Text your **User Code** followed by a space and the word **ARM** to your system.



Depending on the status of your system you will receive one of the following confirmation messages;  
**Confirmed System Armed** or  
**System Already Armed** or  
**System Not Ready to Arm**

Notes:

- 1) If you prefer, the word **SET** can be used instead of **ARM**
- 2) Part arm your system by texting **User Code** followed by **ARM A** or **ARM B**
- 3) When sending commands, we strongly recommend that you turn off the predictive text feature on your phone.

## Unsetting your system

Text your **User Code** followed by a space and the word **UNSET** to your system.



Depending on the status of your system you will receive one of the following confirmation messages;  
**Confirmed System Unset** or  
**System Already Unset**

Note: If you prefer, the word **DISARM** can be used instead of **UNSET**

## Requesting the log of recent events

Text your **User Code** followed by a space, then the word **LOG** followed by another space and the number of log events (between **1** and **21**) to your system.



Depending on how many log events you request this command might involve several text messages from the system to your phone

Note: **2222 LOG** will send the last 7 log events.

*2222 is being used as a User code for illustrative purposes only*

## Getting the current status of your system

Text your **User Code** followed by a space and the word **STATUS** to your system.



Depending on the status of your system you will receive the following types of messages;  
**System Armed / Unset**  
**GSM Signal 80%** etc.

Note: If you prefer, the word **STAT** can be used instead of **STATUS**

## Get the list of commands sent to your phone

Text your **User Code** followed by a space and the word **HELP** to your system.



You will receive a list of the commands;  
Code **ARM/UNSET/FORCE**  
Code **STATUS**  
Code **LOG**

*2222 is being used as a User code for illustrative purposes only*